

**Model:** FDL-250T

**No.** 509

**Subject:** UHF Red Bar Display Bent

**Date:** November 27, 2000



**Symptom:**  
(113X)

UHF red channel bar becomes bent as volume is increased.

**Solution:** If the customer should complain of the symptom above please perform the following.

Serial number range affective 4000001 through 4004700

Ref	Schematic Location	Description Former	Description New	P/N
C625	I-5	Not used originally	10uf/6,3v	1-104-851-11
R010	F-7	27 Ohm	10 Ohm	1-216-001-00
R613	I-5	10K 1/16W	22K 1/16W	1-216-837-11
R614	I-5	10K 1/16W	22K 1/16 W	1-216-837-11



Add 10uf cap between Q604 base (+) and ground (-)

