



<http://www.adadepot.com>

FINAL PHASE  
30-188P  
Miscellaneous Parts  
1 November 1979

FINAL PHASE  
30-188P  
Resistors for Drawing No. 1087  
11/1/79

J1 0.4" jumper or 1 ohm resistor  
J2 wire, 7" 22/7 Nabond  
J3 wire, 8" 22/7 Nabond  
J4 wire, 7" 22/7 Nabond  
J5 0.4" jumper or 1 ohm resistor  
J6 0.4" jumper or 1 ohm resistor  
J7 0.4" jumper or 1 ohm resistor  
J8 wire, 8" 22/7 Nabond  
J9 0.4" jumper or 1 ohm resistor  
J10 0.4" jumper or 1 ohm resistor  
J11 0.4" jumper or 1 ohm resistor  
J12 0.4" jumper or 1 ohm resistor  
J13 0.4" jumper or 1 ohm resistor  
J14 0.2" jumper, 22 awg minimum. For 240 volt operation mod. only.

D1 1N914 diode or 1N4148 diode  
D2 1N914 diode or 1N4148 diode  
D3 1N914 diode or 1N4148 diode  
D4 1N914 diode or 1N4148 diode  
D5 1N4001 diode  
D6 1N4001 diode  
D7 1N4001 diode  
D8 1N4001 diode

T1 B20K 10 mm trimmer, Tsubame 9M-4  
T2 B20K 10 mm trimmer, Tsubame 9M-4  
T3 B20K 10 mm trimmer, Tsubame 9M-4

P1 B50K Tsubame 179P-N2  
P2 B10K Tsubame 179P-N2  
P3 B50K Tsubame 179P-N2  
P4 C500K Tsubame 179P-N2  
P5 B50K Tsubame 179P-N2

IC1 TLO71CP  
IC2 RC3403ADB  
IC3 RC3403ADB  
IC4 RC3403ADB  
IC5 LM324CN  
IC6 MC1458CP1  
IC7 CD4007UBE  
IC8 CD4047BE  
IC9 CD4016BE  
IC10 CD4016BE  
IC11 uA78M15 or 78L15 for AC/DC converter operation only.

R1	1K	R46	220K
R2	4.7K	R47	20K 1%
R3	47K	R48	20K 1%
R4	68K	R49	2K 1%
R5	68K	R50	15K
R6	47	R51	15K
R7	1Meg	R52	1K
R8	10K	R53	20K 1%
R9	300K	R54	20K 1%
R10	10K	R55	2K 1%
R11	36K	R56	220K
R12	150K	R57	20K 1%
R13	150K	R58	110K
R14	1.5K	R59	60.4K 1%
R15	220K	R60	220K
R16	220K	R61	220K
R17	220K	R62	36K
R18	27K	R63	16K
R19	10K	R64	68K
R20	47K	R65	100K
R21	150K	R66	51K
R22	20K 1%	R67	47
R23	20K 1%	R68	22K
R24	2K 1%	R69	100K
R25	15K	R70	150K
R26	15K	R71	510K
R27	1K	R72	1M
R28	20K 1%	R73	47K
R29	20K 1%	R74	150K
R30	2K 1%	R75	47K
R31	20K 1%	R76	47K
R32	20K 1%	R77	2.7K
R33	2K 1%	R78	51K
R34	15K	R79	2K
R35	15K	R80	68K
R36	1K	R81	100K
R37	20K 1%	R82	27K
R38	20K 1%	R83	47
R39	2K 1%	R84	47K
R40	47	R85	27K
R41	220K	R86	10K
R42	20K 1%	R87	47
R43	110K 1%	R88	1M
R44	60.4K 1%	R89	200
R45	220K	R90	47